



VHF P25 CONVENTIONAL & TRUNKED TRANSCEIVER

IC-F9511HT

High Power Mobile for the First Responder!

- P25 Conventional w/Trunking Option
- AES/DES Encryption (Option)
- Enhanced Vocoder Ready
- 110W Output Power
- 512 Channels
128 Zone
- Dual-head Configuration (Option)



High-Power **110W**

Photo includes optional RMK-4, OPC-609 and SP-30

High Power Mobile for the First Responder!

Ready for: P25 conventional, P25 trunking and analog conventional. All in one radio!

VHF P25 CONVENTIONAL & TRUNKED TRANSCEIVER

IC-F9511HT

110W
High-Power



P25 Conventional & Trunking Features

P25 VHF Conventional and Trunking

The IC-9511HT series offers both analog conventional and P25 digital conventional operation with a P25 trunking option. You can assign individual channels to analog conventional, P25 conventional or P25 trunking, all within one radio using digital/analog mixed mode operation.

Interoperability

The IC-F9511HT conforms to standard specifications for TIA/EIA-102, CAAB, Digital C4FM Transceiver Performance Recommendations. Provides interoperability with other brand P25 equipment for public safety applications. The IC-9511HT series is also P25 CAP compliant.

Individual ID and talkgroup ID

The IC-F9511HT has a 100 individual ID and 250 talkgroup ID memories. Use the display to visually select the person or group you're going to call.

Optional AES/DES encryption

AES and DES encryption keeps conversations secure with the optional AES/DES or DES encryption unit. An optional FIPS AES board is certified to FIPS 140-2.

OTAR (Over-the-Air-Rekeying)

The IC-F9511HT supports P25 OTAR and trunked OTAR for changing encryption keys over the air.

Enhanced vocoder ready

Uses the DVSI's AMBE+2™ vocoder.

ATG (Announcement talkback group)

Call a large group of groups on a trunking network. Dispatcher can hear replies when radios respond to an announcement group call.

ESN programming

Save ESN's on a cloning file to only allow approved radios on trunking systems.



110W of powerful RF output

A full 110W of output power is available for reliable long distance communication. A large heat sink provides effective cooling mechanism allowing continuous duty cycle operation (20% duty cycle transmission).

IP54 dust and water resistance

The controller and RF unit have IP54 dust-protection and splash resistance allowing it to be used in wet and dusty conditions.

Dot matrix, multi-function LCD

With a high contrast dot matrix display, upper and lower case characters can be easily distinguished. The display shows 12 characters by 2 lines. LCD backlight is standard.



Vote Scan

The conventional voting mode scan detects the signal strength level of repeater stations and automatically selects the strongest station, useful for roaming between 2 or more repeater sites. Once you program the voting mode to a memory zone, you can easily start voting mode operation by changing the zone setting.

9-pin external speaker connector

The IC-F9511HT has a 9-pin speaker connector with a 15W (typ.) audio amplifier for connecting the SP-30 external speaker, horn honk and ignition sensing line, etc.. When an external loud speaker is connected, the RX speaker function allows you to relay the received audio over the loud speaker.



Photo includes optional RMK-4, OPC-607, SP-22, SP-30 and HM-148G.

Optional dual-head controller*

By installing the optional RMK-4 with a separation cable, the IC-F9511HT can be made a two controller "Dual-head" configuration. While a dual-head operator is communicating using one of the controllers, the other operator can monitor incoming and outgoing audio. Also, the radio can be used as an intercom between controllers.

* Optional dual-head separation kit, separation cable, microphone and speaker are required.

512 memory channels, 128 zones

Up to 512 memory channels can be divided into 128 memory zones, allowing you flexible channel and communication group management. The CTCSS and DTCS encoder and decoder* are also built-in to set up your own talk groups.

* Analog mode only.

Programmable accessory connector

The IC-F9511HT has a D-SUB 25-pin ACC connector for connecting external devices. It has reserved pins for programming to input operating channels, turn on/off functions and output received audio.



Internal clock setting example

Tactical group function

The tactical group function allows you to copy memory channels to the tactical zone and temporarily regroup memory channels. Using the optional zone copy cable, memory channels in the tactical zone can be transferred from a master radio to other radios.

Abundant scanning functions

The dual priority scan monitors two primary channels alternately, while scanning other channels. The mode dependent scan function automatically changes the scan list according to the operating channel setting. The talk back function with timer beep, TX channel and cancel channel settings allow you to preset the transmission channel when you push the PTT button during a scanning operation or cancel the scanning.

Radio stun/kill and Power-on password function

The radio stun/kill function* disables a lost or stolen radio over the air, eliminating security threats from undesired listeners. The power-on password** prevents unauthorized people from turning on the radio.

* P25 digital mode only. ** The power-on password function is not compatible with the RMK-4.

Optional external speaker SP-30

Newly designed external speaker, SP-30 offers 15W* (typ.) of high level audio with the IC-F9511HT for improved operation in noisy environments.

* Rated input of the SP-30 is 20W.

Other features

- Wide frequency coverage (136–174MHz)
 - FM wide/narrow channel spacing*¹
 - Built-in audio compander*¹
 - Built-in inversion type voice scrambler*¹
 - NTIA VHF specification compliant
 - Talk around function
 - DTMF autodial*¹
 - Microphone hanger action (On hook scan and off hook monitor)
 - 2-Tone encoder and decoder*¹ and MDC 1200 compatible*¹
- *¹ Analog mode only



SPECIFICATIONS

GENERAL

- Frequency range : 136-174MHz
- Number of channels : Max. 512 channels/128 zones
- Channel spacing : 15/30kHz (analog) 12.5kHz (digital)
- PLL channel step : 2.5kHz, 3.125kHz
- Emission designators : Analog (wide/narrow) 16K0F3E/11K0F3E Digital 8K10F1E, 8K10F1D
- Antenna impedance : 50Ω (SO-239)
- Operating Temp. range : -30°C to +60°C ; -22°F to +140°F
- Power supply requirement : 13.6V DC nominal
- Current drain (approx.) : Tx High (110W) 22.0A Rx Max. audio 3.0A Stand-by 400mA
- Dimensions (WxHxD) (projections not included) : RF unit 175x60x279 mm; 6.89x2.36x10.98 in Controller 175x45x50.3 mm; 6.89x1.77x1.98 in
- Weight (approx.) : 4.1kg; 9.0lb With controller & cable 4.7kg; 10.4lb Controller 260g; 9.2oz

TRANSMITTER

- Output power (approx) : 110W
- Max. frequency deviation : ±5.0/2.5kHz (Wide/Narrow) Maximum pattern ±2.85kHz (Digital)
- Frequency error : ±1.0ppm
- Spurious emissions : 70dB min.
- Adjacent channel power : 70/60dB min. (Wide/Narrow) 67dB min. (Digital)
- FM hum and noise : 48/45dB typ. (Wide/Narrow)
- Audio harmonic distortion: 3% typ. (40% deviation)
- Ext. microphone impedance : 600Ω (8-pin modular)

Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810 F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4	I, II
Temperature Shock	503.4	I
Solar Radiation	505.4	I
Rain	506.4	I, III
Humidity	507.4	-
Salt Fog	509.4	-
Dust	510.4	I
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.
Ingress Protection Standard
 Dust & Water IP54 (Dust-protection and water resistant)
 When an external speaker is connected to the controller, the controller does not have IP54 protection.

RECEIVER

- Sensitivity : Analog 0.25μV typ. (at 12dB SINAD) Digital 0.25μV typ. (at 5% BER)
- Squelch sensitivity : 0.25μV typ. (at threshold)
- Adjacent Ch. selectivity : Analog (TIA/EIA603B) 81/53dB typ. (Wide/narrow) (TIA/EIA603) 85/77dB typ. (Wide/narrow) Digital 63dB typ.
- Spurious response : 85dB min.
- Intermodulation : 78dB typ.
- Hum and noise ratio : 55/51dB typ. (Wide/Narrow) 52dB typ. (Digital)
- Audio output power : 15W typ. at 3% distortion (with external speaker) with a 4Ω load

Supplied Accessories

- Hand microphone, HM-148G
- Separation cable, 5m (16.4ft)
- Microphone hanger
- Mounting bracket kit for main unit and controller
- Fuse
- Crimp terminals
- Socket terminals
- Cable with fuse holder
- Controller unit
- DC power cable
- Key assign stickers
- * Speaker is an option.

Measurements made in accordance with TIA-102 (Digital), TIA-603B (Wide/narrow). All stated specifications are subject to change without notice or obligation.

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

HAND MICROPHONES



- HM-152** : Regular hand microphone.
- HM-152T** : DTMF microphone.
- HM-148G** : Heavy duty microphone. Self-grounding type. Same as supplied.
- HM-148T** : Heavy duty microphone with DTMF keypad. Self-grounding type.

DUAL-HEAD SEPARATION KIT



For dual-head configuration. Separation cable, microphone and speaker are required separately.

SEPARATION CABLES



- OPC-609** : 1.9m; 6.2ft separation cable.
- OPC-607** : 3.0m; 9.8ft separation cable.
- OPC-726** : 5.0m; 16.4ft separation cable. Same as supplied with the IC-F9511HT.
- OPC-608** : 8.0m; 26.2ft separation cable.

DESKTOP MICROPHONE SM-26




SM-26 : Convenient for dispatching, equipped with monitor switch. **SM-25** is also available.

EXTERNAL SPEAKERS



- SP-30**: External speaker for connection with the RF unit. 20W rated input power. Speaker plug adapter is supplied for connection with the controller.
- SP-35**: External speaker for connection with the controller.

ENCRYPTION UNITS



- UT-125**: Provides AES and DES encryption capabilities. FIPS version available.
- UT-128**: Provides DES encryption capabilities.

ZONE COPY CABLES



- OPC-1532**: Mobile to mobile zone copy cable.
- OPC-1871**: Mobile to handheld zone copy cable.

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia, Japan and/or other countries. AMBE+2 is a trademark and property of Digital Voice Systems Inc. TM: A Certification Mark of NIST, which does not imply product endorsement by NIST, the U.S. or Canadian Governments. All other trademarks are the properties of their respective holders.

Icom Inc.

1-1-32, Kami-minami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icom.co.jp/world

Count on us!

Your local distributor/dealer:

Icom America Inc.

12421 Willows Road NE, Kirkland, WA 98034, U.S.A. Phone: +1 (425) 454-8155 Fax: +1 (425) 454-1509 E-mail: sales@icomamerica.com URL: <http://www.icomamerica.com>

Icom (Europe) GmbH

Communication Equipment Auf der Krautweide 24, 65812 Bad Soden am Taunus, Germany Phone: +49 (6196) 76685-0 Fax: +49 (6196) 76685-50 E-mail: info@icom-europe.com URL: <http://www.icomeurope.com>

Icom France s.a.s.

Zac de la Plaine, 1 Rue Brindejonc des Moulinais, BP 45804, 31505 Toulouse Cedex 5, France Phone: +33 (5) 61 36 03 03 Fax: +33 (5) 61 36 03 00 E-mail: icom@icom-france.com URL: <http://www.icom-france.com>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road, Taipei, Taiwan, R.O.C. Phone: +886 (02) 2559 1899 Fax: +886 (02) 2559 1874 E-mail: sales@asia-icom.com URL: <http://www.asia-icom.com>

Icom Canada

Glenwood Centre #150-6165 Highway 17A, Delta, B.C., V4K 5B8, Canada Phone: +1 (604) 952-4266 Fax: +1 (604) 952-0090 E-mail: info@icomcanada.com URL: <http://www.icomcanada.com>

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer" Bajos A 08174, Sant Cugat del Valles, Barcelona, Spain Phone: +34 (93) 590 26 70 Fax: +34 (93) 589 04 46 E-mail: icom@icomspain.com URL: <http://www.icomspain.com>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road, Clayton, VIC 3168 Australia Phone: +61 (03) 9549 7500 Fax: +61 (03) 9549 7505 E-mail: sales@icom.net.au URL: <http://www.icom.net.au>

Shanghai Icom Ltd.

No.101, Building 9, Caifuxingyuan Park, No.188 Maoting Road, Chedun Town, Songjiang District, Shanghai, 201611, China Phone: +86 (021) 6153 2768 Fax: +86 (021) 5765 9987 E-mail: bjicom@bjicom.com URL: <http://www.bjicom.com>

Icom Brazil

Rua Itororó, 444 Padre Eustáquio Belo Horizonte MG, CEP: 30720-450, Brazil Phone: +55 (31) 3582 8847 Fax: +55 (31) 3582 8987 E-mail: sales@icombrasil.com

Icom (UK) Ltd.

Blacksole House, Altira Park, Herne Bay, Kent, CT6 6GZ, U.K. Phone: +44 (0) 1227 741741 Fax: +44 (0) 1227 741742 E-mail: info@icomuk.co.uk URL: <http://www.icomuk.co.uk>

Icom New Zealand

39C Rennie Drive, Airport Oaks, Auckland, New Zealand Phone: +64 (09) 274 4062 Fax: +64 (09) 274 4708 E-mail: inquiries@icom.co.nz URL: <http://www.icom.co.nz>